

OMRON PLC Harnesses 欧姆龙PLC线束

CJ系列线束 印字表

CJ1W-ID231用 GPN-CJ24□ GPP-CJ24L□ 输入连接器 mCH (m+1)CH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>IN00,m</td><td>1</td><td>1</td><td>IN00,m+1</td></tr><tr><td>IN01,m</td><td>2</td><td>2</td><td>IN01,m+1</td></tr><tr><td>IN02,m</td><td>3</td><td>3</td><td>IN02,m+1</td></tr><tr><td>IN03,m</td><td>4</td><td>4</td><td>IN03,m+1</td></tr><tr><td>IN04,m</td><td>5</td><td>5</td><td>IN04,m+1</td></tr><tr><td>IN05,m</td><td>6</td><td>6</td><td>IN05,m+1</td></tr><tr><td>IN06,m</td><td>7</td><td>7</td><td>IN06,m+1</td></tr><tr><td>IN07,m</td><td>8</td><td>8</td><td>IN07,m+1</td></tr><tr><td>COM0,A</td><td>9</td><td>9</td><td>COM1,A</td></tr><tr><td>IN08,m</td><td>10</td><td>10</td><td>IN08,m+1</td></tr><tr><td>IN09,m</td><td>11</td><td>11</td><td>IN09,m+1</td></tr><tr><td>IN10,m</td><td>12</td><td>12</td><td>IN10,m+1</td></tr><tr><td>IN11,m</td><td>13</td><td>13</td><td>IN11,m+1</td></tr><tr><td>IN12,m</td><td>14</td><td>14</td><td>IN12,m+1</td></tr><tr><td>IN13,m</td><td>15</td><td>15</td><td>IN13,m+1</td></tr><tr><td>IN14,m</td><td>16</td><td>16</td><td>IN14,m+1</td></tr><tr><td>IN15,m</td><td>17</td><td>17</td><td>IN15,m+1</td></tr><tr><td>COM0,B</td><td>18</td><td>18</td><td>COM1,B</td></tr><tr><td></td><td>19</td><td>19</td><td></td></tr><tr><td></td><td>20</td><td>20</td><td></td></tr></table> FCN插针40芯	信号名	A	B	信号名	IN00,m	1	1	IN00,m+1	IN01,m	2	2	IN01,m+1	IN02,m	3	3	IN02,m+1	IN03,m	4	4	IN03,m+1	IN04,m	5	5	IN04,m+1	IN05,m	6	6	IN05,m+1	IN06,m	7	7	IN06,m+1	IN07,m	8	8	IN07,m+1	COM0,A	9	9	COM1,A	IN08,m	10	10	IN08,m+1	IN09,m	11	11	IN09,m+1	IN10,m	12	12	IN10,m+1	IN11,m	13	13	IN11,m+1	IN12,m	14	14	IN12,m+1	IN13,m	15	15	IN13,m+1	IN14,m	16	16	IN14,m+1	IN15,m	17	17	IN15,m+1	COM0,B	18	18	COM1,B		19	19			20	20		CJ1W-ID261用 GPN-CJ25□ GPP-CJ25L□ 输入连接器1 m+1CH mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>IN15,m+1</td><td>17</td><td>17</td><td>IN15,m</td></tr><tr><td>IN14,m+1</td><td>16</td><td>16</td><td>IN14,m</td></tr><tr><td>IN13,m+1</td><td>15</td><td>15</td><td>IN13,m</td></tr><tr><td>IN12,m+1</td><td>14</td><td>14</td><td>IN12,m</td></tr><tr><td>IN11,m+1</td><td>13</td><td>13</td><td>IN11,m</td></tr><tr><td>IN10,m+1</td><td>12</td><td>12</td><td>IN10,m</td></tr><tr><td>IN09,m+1</td><td>11</td><td>11</td><td>IN09,m</td></tr><tr><td>IN08,m+1</td><td>10</td><td>10</td><td>IN08,m</td></tr><tr><td>COM1,A</td><td>9</td><td>9</td><td>COM0,A</td></tr><tr><td>IN07,m+1</td><td>8</td><td>8</td><td>IN07,m</td></tr><tr><td>IN06,m+1</td><td>7</td><td>7</td><td>IN06,m</td></tr><tr><td>IN05,m+1</td><td>6</td><td>6</td><td>IN05,m</td></tr><tr><td>IN04,m+1</td><td>5</td><td>5</td><td>IN04,m</td></tr><tr><td>IN03,m+1</td><td>4</td><td>4</td><td>IN03,m</td></tr><tr><td>IN02,m+1</td><td>3</td><td>3</td><td>IN02,m</td></tr><tr><td>IN01,m+1</td><td>2</td><td>2</td><td>IN01,m</td></tr><tr><td>IN00,m+1</td><td>1</td><td>1</td><td>IN00,m</td></tr></table> FCN插针40芯	信号名	A	B	信号名	IN15,m+1	17	17	IN15,m	IN14,m+1	16	16	IN14,m	IN13,m+1	15	15	IN13,m	IN12,m+1	14	14	IN12,m	IN11,m+1	13	13	IN11,m	IN10,m+1	12	12	IN10,m	IN09,m+1	11	11	IN09,m	IN08,m+1	10	10	IN08,m	COM1,A	9	9	COM0,A	IN07,m+1	8	8	IN07,m	IN06,m+1	7	7	IN06,m	IN05,m+1	6	6	IN05,m	IN04,m+1	5	5	IN04,m	IN03,m+1	4	4	IN03,m	IN02,m+1	3	3	IN02,m	IN01,m+1	2	2	IN01,m	IN00,m+1	1	1	IN00,m	CJ1W-ID261用 GPN-CJ26□ GPP-CJ26L□ 输入连接器2 m+2CH m+3CH mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>IN00,m+2</td><td>20</td><td>20</td><td>IN00,m+3</td></tr><tr><td>IN01,m+2</td><td>21</td><td>21</td><td>IN01,m+3</td></tr><tr><td>IN02,m+2</td><td>22</td><td>22</td><td>IN02,m+3</td></tr><tr><td>IN03,m+2</td><td>23</td><td>23</td><td>IN03,m+3</td></tr><tr><td>IN04,m+2</td><td>24</td><td>24</td><td>IN04,m+3</td></tr><tr><td>IN05,m+2</td><td>25</td><td>25</td><td>IN05,m+3</td></tr><tr><td>IN06,m+2</td><td>26</td><td>26</td><td>IN06,m+3</td></tr><tr><td>IN07,m+2</td><td>27</td><td>27</td><td>IN07,m+3</td></tr><tr><td>IN08,m+2</td><td>28</td><td>28</td><td>IN08,m+3</td></tr><tr><td>IN09,m+2</td><td>29</td><td>29</td><td>IN09,m+3</td></tr><tr><td>IN10,m+2</td><td>30</td><td>30</td><td>IN10,m+3</td></tr><tr><td>IN11,m+2</td><td>31</td><td>31</td><td>IN11,m+3</td></tr><tr><td>IN12,m+2</td><td>32</td><td>32</td><td>IN12,m+3</td></tr><tr><td>IN13,m+2</td><td>33</td><td>33</td><td>IN13,m+3</td></tr><tr><td>IN14,m+2</td><td>34</td><td>34</td><td>IN14,m+3</td></tr><tr><td>IN15,m+2</td><td>35</td><td>35</td><td>IN15,m+3</td></tr><tr><td>COM2,B</td><td>36</td><td>36</td><td>COM3,B</td></tr><tr><td></td><td>37</td><td>37</td><td></td></tr><tr><td></td><td>38</td><td>38</td><td></td></tr><tr><td></td><td>39</td><td>39</td><td></td></tr><tr><td></td><td>40</td><td>40</td><td></td></tr></table> FCN插针40芯	信号名	A	B	信号名	IN00,m+2	20	20	IN00,m+3	IN01,m+2	21	21	IN01,m+3	IN02,m+2	22	22	IN02,m+3	IN03,m+2	23	23	IN03,m+3	IN04,m+2	24	24	IN04,m+3	IN05,m+2	25	25	IN05,m+3	IN06,m+2	26	26	IN06,m+3	IN07,m+2	27	27	IN07,m+3	IN08,m+2	28	28	IN08,m+3	IN09,m+2	29	29	IN09,m+3	IN10,m+2	30	30	IN10,m+3	IN11,m+2	31	31	IN11,m+3	IN12,m+2	32	32	IN12,m+3	IN13,m+2	33	33	IN13,m+3	IN14,m+2	34	34	IN14,m+3	IN15,m+2	35	35	IN15,m+3	COM2,B	36	36	COM3,B		37	37			38	38			39	39			40	40		CJ1W-OD231用 GPN-CJ29□ GPP-CJ29L□ 输出连接器 mCH (m+1)CH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>OUT03,m</td><td>1</td><td>1</td><td>OUT03,m+1</td></tr><tr><td>OUT01,m</td><td>2</td><td>2</td><td>OUT01,m+1</td></tr><tr><td>OUT02,m</td><td>3</td><td>3</td><td>OUT02,m+1</td></tr><tr><td>OUT03,m</td><td>4</td><td>4</td><td>OUT03,m+1</td></tr><tr><td>OUT04,m</td><td>5</td><td>5</td><td>OUT04,m+1</td></tr><tr><td>OUT05,m</td><td>6</td><td>6</td><td>OUT05,m+1</td></tr><tr><td>OUT06,m</td><td>7</td><td>7</td><td>OUT06,m+1</td></tr><tr><td>OUT07,m</td><td>8</td><td>8</td><td>OUT07,m+1</td></tr><tr><td>COM0,A</td><td>9</td><td>9</td><td>COM1,A</td></tr><tr><td>+V,A</td><td>10</td><td>10</td><td>+V,B</td></tr><tr><td>OUT08,m</td><td>11</td><td>11</td><td>OUT08,m+1</td></tr><tr><td>OUT09,m</td><td>12</td><td>12</td><td>OUT09,m+1</td></tr><tr><td>OUT10,m</td><td>13</td><td>13</td><td>OUT10,m+1</td></tr><tr><td>OUT11,m</td><td>14</td><td>14</td><td>OUT11,m+1</td></tr><tr><td>OUT12,m</td><td>15</td><td>15</td><td>OUT12,m+1</td></tr><tr><td>OUT13,m</td><td>16</td><td>16</td><td>OUT13,m+1</td></tr><tr><td>OUT14,m</td><td>17</td><td>17</td><td>OUT14,m+1</td></tr><tr><td>OUT15,m</td><td>18</td><td>18</td><td>OUT15,m+1</td></tr><tr><td>COM0,B</td><td>19</td><td>19</td><td>COM1,B</td></tr><tr><td>+V,C</td><td>20</td><td>20</td><td>+V,D</td></tr></table> FCN插针40芯	信号名	A	B	信号名	OUT03,m	1	1	OUT03,m+1	OUT01,m	2	2	OUT01,m+1	OUT02,m	3	3	OUT02,m+1	OUT03,m	4	4	OUT03,m+1	OUT04,m	5	5	OUT04,m+1	OUT05,m	6	6	OUT05,m+1	OUT06,m	7	7	OUT06,m+1	OUT07,m	8	8	OUT07,m+1	COM0,A	9	9	COM1,A	+V,A	10	10	+V,B	OUT08,m	11	11	OUT08,m+1	OUT09,m	12	12	OUT09,m+1	OUT10,m	13	13	OUT10,m+1	OUT11,m	14	14	OUT11,m+1	OUT12,m	15	15	OUT12,m+1	OUT13,m	16	16	OUT13,m+1	OUT14,m	17	17	OUT14,m+1	OUT15,m	18	18	OUT15,m+1	COM0,B	19	19	COM1,B	+V,C	20	20	+V,D	CJ1W-ID232用 GPN-CJ48□ GPP-CJ48□ 输入连接器 (m+1)CH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>COM1,A</td><td>1</td><td>2</td><td>COM1,B</td></tr><tr><td>OV,A</td><td>3</td><td>4</td><td>OV,B</td></tr><tr><td>IN15,m+1</td><td>5</td><td>6</td><td>IN07,m+1</td></tr><tr><td>IN14,m+1</td><td>7</td><td>8</td><td>IN06,m+1</td></tr><tr><td>IN13,m+1</td><td>9</td><td>10</td><td>IN05,m+1</td></tr><tr><td>IN12,m+1</td><td>11</td><td>12</td><td>IN04,m+1</td></tr><tr><td>IN11,m+1</td><td>13</td><td>14</td><td>IN03,m+1</td></tr><tr><td>IN10,m+1</td><td>15</td><td>16</td><td>IN02,m+1</td></tr><tr><td>IN09,m+1</td><td>17</td><td>18</td><td>IN01,m+1</td></tr><tr><td>IN08,m+1</td><td>19</td><td>20</td><td>IN00,m+1</td></tr><tr><td>COM0,A</td><td>21</td><td>22</td><td>COM0,B</td></tr><tr><td>OV,C</td><td>23</td><td>24</td><td>OV,D</td></tr><tr><td>OUT15,m</td><td>25</td><td>26</td><td>OUT07,m</td></tr><tr><td>OUT14,m</td><td>27</td><td>28</td><td>OUT06,m</td></tr><tr><td>OUT13,m</td><td>29</td><td>30</td><td>OUT05,m</td></tr><tr><td>OUT12,m</td><td>31</td><td>32</td><td>OUT04,m</td></tr><tr><td>OUT11,m</td><td>33</td><td>34</td><td>OUT03,m</td></tr><tr><td>OUT10,m</td><td>35</td><td>36</td><td>OUT02,m</td></tr><tr><td>OUT09,m</td><td>37</td><td>38</td><td>OUT01,m</td></tr><tr><td>OUT08,m</td><td>39</td><td>40</td><td>OUT00,m</td></tr></table> MIL插针40芯	信号名	A	B	信号名	COM1,A	1	2	COM1,B	OV,A	3	4	OV,B	IN15,m+1	5	6	IN07,m+1	IN14,m+1	7	8	IN06,m+1	IN13,m+1	9	10	IN05,m+1	IN12,m+1	11	12	IN04,m+1	IN11,m+1	13	14	IN03,m+1	IN10,m+1	15	16	IN02,m+1	IN09,m+1	17	18	IN01,m+1	IN08,m+1	19	20	IN00,m+1	COM0,A	21	22	COM0,B	OV,C	23	24	OV,D	OUT15,m	25	26	OUT07,m	OUT14,m	27	28	OUT06,m	OUT13,m	29	30	OUT05,m	OUT12,m	31	32	OUT04,m	OUT11,m	33	34	OUT03,m	OUT10,m	35	36	OUT02,m	OUT09,m	37	38	OUT01,m	OUT08,m	39	40	OUT00,m
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
IN00,m	1	1	IN00,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN01,m	2	2	IN01,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN02,m	3	3	IN02,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN03,m	4	4	IN03,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN04,m	5	5	IN04,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN05,m	6	6	IN05,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN06,m	7	7	IN06,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN07,m	8	8	IN07,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,A	9	9	COM1,A																																																																																																																																																																																																																																																																																																																																																																																																																													
IN08,m	10	10	IN08,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN09,m	11	11	IN09,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN10,m	12	12	IN10,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m	13	13	IN11,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m	14	14	IN12,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m	15	15	IN13,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m	16	16	IN14,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m	17	17	IN15,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,B	18	18	COM1,B																																																																																																																																																																																																																																																																																																																																																																																																																													
	19	19																																																																																																																																																																																																																																																																																																																																																																																																																														
	20	20																																																																																																																																																																																																																																																																																																																																																																																																																														
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m+1	17	17	IN15,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m+1	16	16	IN14,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m+1	15	15	IN13,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m+1	14	14	IN12,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m+1	13	13	IN11,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN10,m+1	12	12	IN10,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN09,m+1	11	11	IN09,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN08,m+1	10	10	IN08,m																																																																																																																																																																																																																																																																																																																																																																																																																													
COM1,A	9	9	COM0,A																																																																																																																																																																																																																																																																																																																																																																																																																													
IN07,m+1	8	8	IN07,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN06,m+1	7	7	IN06,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN05,m+1	6	6	IN05,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN04,m+1	5	5	IN04,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN03,m+1	4	4	IN03,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN02,m+1	3	3	IN02,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN01,m+1	2	2	IN01,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN00,m+1	1	1	IN00,m																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
IN00,m+2	20	20	IN00,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN01,m+2	21	21	IN01,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN02,m+2	22	22	IN02,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN03,m+2	23	23	IN03,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN04,m+2	24	24	IN04,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN05,m+2	25	25	IN05,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN06,m+2	26	26	IN06,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN07,m+2	27	27	IN07,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN08,m+2	28	28	IN08,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN09,m+2	29	29	IN09,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN10,m+2	30	30	IN10,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m+2	31	31	IN11,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m+2	32	32	IN12,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m+2	33	33	IN13,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m+2	34	34	IN14,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m+2	35	35	IN15,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
COM2,B	36	36	COM3,B																																																																																																																																																																																																																																																																																																																																																																																																																													
	37	37																																																																																																																																																																																																																																																																																																																																																																																																																														
	38	38																																																																																																																																																																																																																																																																																																																																																																																																																														
	39	39																																																																																																																																																																																																																																																																																																																																																																																																																														
	40	40																																																																																																																																																																																																																																																																																																																																																																																																																														
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT03,m	1	1	OUT03,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT01,m	2	2	OUT01,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT02,m	3	3	OUT02,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT03,m	4	4	OUT03,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT04,m	5	5	OUT04,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT05,m	6	6	OUT05,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT06,m	7	7	OUT06,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT07,m	8	8	OUT07,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,A	9	9	COM1,A																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,A	10	10	+V,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08,m	11	11	OUT08,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09,m	12	12	OUT09,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10,m	13	13	OUT10,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11,m	14	14	OUT11,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12,m	15	15	OUT12,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13,m	16	16	OUT13,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14,m	17	17	OUT14,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15,m	18	18	OUT15,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,B	19	19	COM1,B																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,C	20	20	+V,D																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
COM1,A	1	2	COM1,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OV,A	3	4	OV,B																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m+1	5	6	IN07,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m+1	7	8	IN06,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m+1	9	10	IN05,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m+1	11	12	IN04,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m+1	13	14	IN03,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN10,m+1	15	16	IN02,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN09,m+1	17	18	IN01,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
IN08,m+1	19	20	IN00,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,A	21	22	COM0,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OV,C	23	24	OV,D																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15,m	25	26	OUT07,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14,m	27	28	OUT06,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13,m	29	30	OUT05,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12,m	31	32	OUT04,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11,m	33	34	OUT03,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10,m	35	36	OUT02,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09,m	37	38	OUT01,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08,m	39	40	OUT00,m																																																																																																																																																																																																																																																																																																																																																																																																																													
CJ1W-OD261用 GPN-CJ32□ GPP-CJ32R□ 输出连接器1 m+1CH mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>+V,D</td><td>20</td><td>20</td><td>+V,C</td></tr><tr><td>COM1,B</td><td>19</td><td>19</td><td>COM0,B</td></tr><tr><td>OUT15,m+1</td><td>18</td><td>18</td><td>OUT15,m</td></tr><tr><td>OUT14,m+1</td><td>17</td><td>17</td><td>OUT14,m</td></tr><tr><td>OUT13,m+1</td><td>16</td><td>16</td><td>OUT13,m</td></tr><tr><td>OUT12,m+1</td><td>15</td><td>15</td><td>OUT12,m</td></tr><tr><td>OUT11,m+1</td><td>14</td><td>14</td><td>OUT11,m</td></tr><tr><td>OUT10,m+1</td><td>13</td><td>13</td><td>OUT10,m</td></tr><tr><td>OUT09,m+1</td><td>12</td><td>12</td><td>OUT09,m</td></tr><tr><td>OUT08,m+1</td><td>11</td><td>11</td><td>OUT08,m</td></tr><tr><td>+V,B</td><td>10</td><td>10</td><td>+V,A</td></tr><tr><td>COM1,A</td><td>9</td><td>9</td><td>COM0,A</td></tr><tr><td>OUT07,m+1</td><td>8</td><td>8</td><td>OUT07,m</td></tr><tr><td>OUT06,m+1</td><td>7</td><td>7</td><td>OUT06,m</td></tr><tr><td>OUT05,m+1</td><td>6</td><td>6</td><td>OUT05,m</td></tr><tr><td>OUT04,m+1</td><td>5</td><td>5</td><td>OUT04,m</td></tr><tr><td>OUT03,m+1</td><td>4</td><td>4</td><td>OUT03,m</td></tr><tr><td>OUT02,m+1</td><td>3</td><td>3</td><td>OUT02,m</td></tr><tr><td>OUT01,m+1</td><td>2</td><td>2</td><td>OUT01,m</td></tr><tr><td>OUT00,m+1</td><td>1</td><td>1</td><td>OUT00,m</td></tr></table> FCN插针40芯	信号名	A	B	信号名	+V,D	20	20	+V,C	COM1,B	19	19	COM0,B	OUT15,m+1	18	18	OUT15,m	OUT14,m+1	17	17	OUT14,m	OUT13,m+1	16	16	OUT13,m	OUT12,m+1	15	15	OUT12,m	OUT11,m+1	14	14	OUT11,m	OUT10,m+1	13	13	OUT10,m	OUT09,m+1	12	12	OUT09,m	OUT08,m+1	11	11	OUT08,m	+V,B	10	10	+V,A	COM1,A	9	9	COM0,A	OUT07,m+1	8	8	OUT07,m	OUT06,m+1	7	7	OUT06,m	OUT05,m+1	6	6	OUT05,m	OUT04,m+1	5	5	OUT04,m	OUT03,m+1	4	4	OUT03,m	OUT02,m+1	3	3	OUT02,m	OUT01,m+1	2	2	OUT01,m	OUT00,m+1	1	1	OUT00,m	CJ1W-OD261用 GPN-CJ33□ GPP-CJ33L□ 输出连接器2 m+2CH m+3CH mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>OUT00,m+2</td><td>21</td><td>21</td><td>OUT00,m+3</td></tr><tr><td>OUT01,m+2</td><td>22</td><td>22</td><td>OUT01,m+3</td></tr><tr><td>OUT02,m+2</td><td>23</td><td>23</td><td>OUT02,m+3</td></tr><tr><td>OUT03,m+2</td><td>24</td><td>24</td><td>OUT03,m+3</td></tr><tr><td>OUT04,m+2</td><td>25</td><td>25</td><td>OUT04,m+3</td></tr><tr><td>OUT05,m+2</td><td>26</td><td>26</td><td>OUT05,m+3</td></tr><tr><td>OUT06,m+2</td><td>27</td><td>27</td><td>OUT06,m+3</td></tr><tr><td>OUT07,m+2</td><td>28</td><td>28</td><td>OUT07,m+3</td></tr><tr><td>COM2,A</td><td>29</td><td>29</td><td>COM3,A</td></tr><tr><td>+V,B</td><td>30</td><td>30</td><td>+V,A</td></tr><tr><td>OUT08,m+2</td><td>31</td><td>31</td><td>OUT08,m+3</td></tr><tr><td>OUT09,m+2</td><td>32</td><td>32</td><td>OUT09,m+3</td></tr><tr><td>OUT10,m+2</td><td>33</td><td>33</td><td>OUT10,m+3</td></tr><tr><td>OUT11,m+2</td><td>34</td><td>34</td><td>OUT11,m+3</td></tr><tr><td>OUT12,m+2</td><td>35</td><td>35</td><td>OUT12,m+3</td></tr><tr><td>OUT13,m+2</td><td>36</td><td>36</td><td>OUT13,m+3</td></tr><tr><td>OUT14,m+2</td><td>37</td><td>37</td><td>OUT14,m+3</td></tr><tr><td>OUT15,m+2</td><td>38</td><td>38</td><td>OUT15,m+3</td></tr><tr><td>COM2,B</td><td>39</td><td>39</td><td>COM3,B</td></tr><tr><td>+V,C</td><td>40</td><td>40</td><td>+V,D</td></tr></table> FCN插针40芯	信号名	A	B	信号名	OUT00,m+2	21	21	OUT00,m+3	OUT01,m+2	22	22	OUT01,m+3	OUT02,m+2	23	23	OUT02,m+3	OUT03,m+2	24	24	OUT03,m+3	OUT04,m+2	25	25	OUT04,m+3	OUT05,m+2	26	26	OUT05,m+3	OUT06,m+2	27	27	OUT06,m+3	OUT07,m+2	28	28	OUT07,m+3	COM2,A	29	29	COM3,A	+V,B	30	30	+V,A	OUT08,m+2	31	31	OUT08,m+3	OUT09,m+2	32	32	OUT09,m+3	OUT10,m+2	33	33	OUT10,m+3	OUT11,m+2	34	34	OUT11,m+3	OUT12,m+2	35	35	OUT12,m+3	OUT13,m+2	36	36	OUT13,m+3	OUT14,m+2	37	37	OUT14,m+3	OUT15,m+2	38	38	OUT15,m+3	COM2,B	39	39	COM3,B	+V,C	40	40	+V,D	CJ1W-MD231用 GPN-CJ22□ 输出连接器 mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>IN00</td><td>12</td><td>12</td><td>IN08</td></tr><tr><td>IN01</td><td>11</td><td>11</td><td>IN07</td></tr><tr><td>IN02</td><td>10</td><td>10</td><td>IN06</td></tr><tr><td>IN03</td><td>9</td><td>9</td><td>IN05</td></tr><tr><td>IN04</td><td>8</td><td>8</td><td>IN04</td></tr><tr><td>IN05</td><td>7</td><td>7</td><td>IN03</td></tr><tr><td>IN06</td><td>6</td><td>6</td><td>IN02</td></tr><tr><td>IN07</td><td>5</td><td>5</td><td>IN01</td></tr><tr><td>COM0,B</td><td>4</td><td>4</td><td>COM0,A</td></tr><tr><td>OUT15</td><td>3</td><td>3</td><td>OUT14</td></tr><tr><td>OUT14</td><td>2</td><td>2</td><td>OUT13</td></tr><tr><td>OUT13</td><td>1</td><td>1</td><td>OUT12</td></tr><tr><td>OUT12</td><td>0</td><td>0</td><td>OUT11</td></tr><tr><td>OUT11</td><td>0</td><td>0</td><td>OUT10</td></tr><tr><td>OUT10</td><td>0</td><td>0</td><td>OUT09</td></tr><tr><td>OUT09</td><td>0</td><td>0</td><td>OUT08</td></tr><tr><td>OUT08</td><td>0</td><td>0</td><td>OUT07</td></tr></table> FCN插针24芯	信号名	A	B	信号名	IN00	12	12	IN08	IN01	11	11	IN07	IN02	10	10	IN06	IN03	9	9	IN05	IN04	8	8	IN04	IN05	7	7	IN03	IN06	6	6	IN02	IN07	5	5	IN01	COM0,B	4	4	COM0,A	OUT15	3	3	OUT14	OUT14	2	2	OUT13	OUT13	1	1	OUT12	OUT12	0	0	OUT11	OUT11	0	0	OUT10	OUT10	0	0	OUT09	OUT09	0	0	OUT08	OUT08	0	0	OUT07	CJ1W-MD231用 GPN-CJ23□ 输入连接器 m+1CH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>IN00</td><td>1</td><td>1</td><td>IN08</td></tr><tr><td>IN01</td><td>2</td><td>2</td><td>IN07</td></tr><tr><td>IN02</td><td>3</td><td>3</td><td>IN06</td></tr><tr><td>IN03</td><td>4</td><td>4</td><td>IN05</td></tr><tr><td>IN04</td><td>5</td><td>5</td><td>IN04</td></tr><tr><td>IN05</td><td>6</td><td>6</td><td>IN03</td></tr><tr><td>IN06</td><td>7</td><td>7</td><td>IN02</td></tr><tr><td>IN07</td><td>8</td><td>8</td><td>IN01</td></tr><tr><td>COM0,A</td><td>9</td><td>9</td><td>COM0,B</td></tr><tr><td>OUT10</td><td>10</td><td>10</td><td>OUT09</td></tr><tr><td>OUT09</td><td>11</td><td>11</td><td>OUT08</td></tr><tr><td>OUT08</td><td>12</td><td>12</td><td>OUT07</td></tr></table> FCN插针24芯	信号名	A	B	信号名	IN00	1	1	IN08	IN01	2	2	IN07	IN02	3	3	IN06	IN03	4	4	IN05	IN04	5	5	IN04	IN05	6	6	IN03	IN06	7	7	IN02	IN07	8	8	IN01	COM0,A	9	9	COM0,B	OUT10	10	10	OUT09	OUT09	11	11	OUT08	OUT08	12	12	OUT07	CJ1W-OD232用 GPN-CJ55□ GPP-CJ55□ 输出连接器 (m+1)CH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>COM1+V,A</td><td>1</td><td>2</td><td>COM1+V,B</td></tr><tr><td>OV,A</td><td>3</td><td>4</td><td>OV,B</td></tr><tr><td>OUT15,m+1</td><td>5</td><td>6</td><td>OUT07,m+1</td></tr><tr><td>OUT14,m+1</td><td>7</td><td>8</td><td>OUT06,m+1</td></tr><tr><td>OUT13,m+1</td><td>9</td><td>10</td><td>OUT05,m+1</td></tr><tr><td>OUT12,m+1</td><td>11</td><td>12</td><td>OUT04,m+1</td></tr><tr><td>OUT11,m+1</td><td>13</td><td>14</td><td>OUT03,m+1</td></tr><tr><td>OUT10,m+1</td><td>15</td><td>16</td><td>OUT02,m+1</td></tr><tr><td>OUT09,m+1</td><td>17</td><td>18</td><td>OUT01,m+1</td></tr><tr><td>OUT08,m+1</td><td>19</td><td>20</td><td>OUT00,m+1</td></tr><tr><td>COM0+V,A</td><td>21</td><td>22</td><td>COM0+V,B</td></tr><tr><td>OV,C</td><td>23</td><td>24</td><td>OV,D</td></tr><tr><td>OUT15,m</td><td>25</td><td>26</td><td>OUT07,m</td></tr><tr><td>OUT14,m</td><td>27</td><td>28</td><td>OUT06,m</td></tr><tr><td>OUT13,m</td><td>29</td><td>30</td><td>OUT05,m</td></tr><tr><td>OUT12,m</td><td>31</td><td>32</td><td>OUT04,m</td></tr><tr><td>OUT11,m</td><td>33</td><td>34</td><td>OUT03,m</td></tr><tr><td>OUT10,m</td><td>35</td><td>36</td><td>OUT02,m</td></tr><tr><td>OUT09,m</td><td>37</td><td>38</td><td>OUT01,m</td></tr><tr><td>OUT08,m</td><td>39</td><td>40</td><td>OUT00,m</td></tr></table> MIL插针40芯	信号名	A	B	信号名	COM1+V,A	1	2	COM1+V,B	OV,A	3	4	OV,B	OUT15,m+1	5	6	OUT07,m+1	OUT14,m+1	7	8	OUT06,m+1	OUT13,m+1	9	10	OUT05,m+1	OUT12,m+1	11	12	OUT04,m+1	OUT11,m+1	13	14	OUT03,m+1	OUT10,m+1	15	16	OUT02,m+1	OUT09,m+1	17	18	OUT01,m+1	OUT08,m+1	19	20	OUT00,m+1	COM0+V,A	21	22	COM0+V,B	OV,C	23	24	OV,D	OUT15,m	25	26	OUT07,m	OUT14,m	27	28	OUT06,m	OUT13,m	29	30	OUT05,m	OUT12,m	31	32	OUT04,m	OUT11,m	33	34	OUT03,m	OUT10,m	35	36	OUT02,m	OUT09,m	37	38	OUT01,m	OUT08,m	39	40	OUT00,m																																				
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,D	20	20	+V,C																																																																																																																																																																																																																																																																																																																																																																																																																													
COM1,B	19	19	COM0,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15,m+1	18	18	OUT15,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14,m+1	17	17	OUT14,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13,m+1	16	16	OUT13,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12,m+1	15	15	OUT12,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11,m+1	14	14	OUT11,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10,m+1	13	13	OUT10,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09,m+1	12	12	OUT09,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08,m+1	11	11	OUT08,m																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,B	10	10	+V,A																																																																																																																																																																																																																																																																																																																																																																																																																													
COM1,A	9	9	COM0,A																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT07,m+1	8	8	OUT07,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT06,m+1	7	7	OUT06,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT05,m+1	6	6	OUT05,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT04,m+1	5	5	OUT04,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT03,m+1	4	4	OUT03,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT02,m+1	3	3	OUT02,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT01,m+1	2	2	OUT01,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT00,m+1	1	1	OUT00,m																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT00,m+2	21	21	OUT00,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT01,m+2	22	22	OUT01,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT02,m+2	23	23	OUT02,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT03,m+2	24	24	OUT03,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT04,m+2	25	25	OUT04,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT05,m+2	26	26	OUT05,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT06,m+2	27	27	OUT06,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT07,m+2	28	28	OUT07,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
COM2,A	29	29	COM3,A																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,B	30	30	+V,A																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08,m+2	31	31	OUT08,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09,m+2	32	32	OUT09,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10,m+2	33	33	OUT10,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11,m+2	34	34	OUT11,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12,m+2	35	35	OUT12,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13,m+2	36	36	OUT13,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14,m+2	37	37	OUT14,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15,m+2	38	38	OUT15,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
COM2,B	39	39	COM3,B																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,C	40	40	+V,D																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
IN00	12	12	IN08																																																																																																																																																																																																																																																																																																																																																																																																																													
IN01	11	11	IN07																																																																																																																																																																																																																																																																																																																																																																																																																													
IN02	10	10	IN06																																																																																																																																																																																																																																																																																																																																																																																																																													
IN03	9	9	IN05																																																																																																																																																																																																																																																																																																																																																																																																																													
IN04	8	8	IN04																																																																																																																																																																																																																																																																																																																																																																																																																													
IN05	7	7	IN03																																																																																																																																																																																																																																																																																																																																																																																																																													
IN06	6	6	IN02																																																																																																																																																																																																																																																																																																																																																																																																																													
IN07	5	5	IN01																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,B	4	4	COM0,A																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15	3	3	OUT14																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14	2	2	OUT13																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13	1	1	OUT12																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12	0	0	OUT11																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11	0	0	OUT10																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10	0	0	OUT09																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09	0	0	OUT08																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08	0	0	OUT07																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
IN00	1	1	IN08																																																																																																																																																																																																																																																																																																																																																																																																																													
IN01	2	2	IN07																																																																																																																																																																																																																																																																																																																																																																																																																													
IN02	3	3	IN06																																																																																																																																																																																																																																																																																																																																																																																																																													
IN03	4	4	IN05																																																																																																																																																																																																																																																																																																																																																																																																																													
IN04	5	5	IN04																																																																																																																																																																																																																																																																																																																																																																																																																													
IN05	6	6	IN03																																																																																																																																																																																																																																																																																																																																																																																																																													
IN06	7	7	IN02																																																																																																																																																																																																																																																																																																																																																																																																																													
IN07	8	8	IN01																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,A	9	9	COM0,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10	10	10	OUT09																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09	11	11	OUT08																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08	12	12	OUT07																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
COM1+V,A	1	2	COM1+V,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OV,A	3	4	OV,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15,m+1	5	6	OUT07,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14,m+1	7	8	OUT06,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13,m+1	9	10	OUT05,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12,m+1	11	12	OUT04,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11,m+1	13	14	OUT03,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10,m+1	15	16	OUT02,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09,m+1	17	18	OUT01,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08,m+1	19	20	OUT00,m+1																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0+V,A	21	22	COM0+V,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OV,C	23	24	OV,D																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15,m	25	26	OUT07,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14,m	27	28	OUT06,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13,m	29	30	OUT05,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12,m	31	32	OUT04,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11,m	33	34	OUT03,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10,m	35	36	OUT02,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09,m	37	38	OUT01,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08,m	39	40	OUT00,m																																																																																																																																																																																																																																																																																																																																																																																																																													
CJ1W-MD261用 GPN-CJ27□ GPP-CJ27R□ 输出连接器 m+1CH mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>+V,D</td><td>20</td><td>20</td><td>+V,C</td></tr><tr><td>COM1,B</td><td>19</td><td>19</td><td>COM0,B</td></tr><tr><td>OUT15,m+1</td><td>18</td><td>18</td><td>OUT15,m</td></tr><tr><td>OUT14,m+1</td><td>17</td><td>17</td><td>OUT14,m</td></tr><tr><td>OUT13,m+1</td><td>16</td><td>16</td><td>OUT13,m</td></tr><tr><td>OUT12,m+1</td><td>15</td><td>15</td><td>OUT12,m</td></tr><tr><td>OUT11,m+1</td><td>14</td><td>14</td><td>OUT11,m</td></tr><tr><td>OUT10,m+1</td><td>13</td><td>13</td><td>OUT10,m</td></tr><tr><td>OUT09,m+1</td><td>12</td><td>12</td><td>OUT09,m</td></tr><tr><td>OUT08,m+1</td><td>11</td><td>11</td><td>OUT08,m</td></tr><tr><td>+V,B</td><td>10</td><td>10</td><td>+V,A</td></tr><tr><td>COM1,A</td><td>9</td><td>9</td><td>COM0,A</td></tr><tr><td>OUT07,m+1</td><td>8</td><td>8</td><td>OUT07,m</td></tr><tr><td>OUT06,m+1</td><td>7</td><td>7</td><td>OUT06,m</td></tr><tr><td>OUT05,m+1</td><td>6</td><td>6</td><td>OUT05,m</td></tr><tr><td>OUT04,m+1</td><td>5</td><td>5</td><td>OUT04,m</td></tr><tr><td>OUT03,m+1</td><td>4</td><td>4</td><td>OUT03,m</td></tr><tr><td>OUT02,m+1</td><td>3</td><td>3</td><td>OUT02,m</td></tr><tr><td>OUT01,m+1</td><td>2</td><td>2</td><td>OUT01,m</td></tr><tr><td>OUT00,m+1</td><td>1</td><td>1</td><td>OUT00,m</td></tr></table> FCN插针40芯	信号名	A	B	信号名	+V,D	20	20	+V,C	COM1,B	19	19	COM0,B	OUT15,m+1	18	18	OUT15,m	OUT14,m+1	17	17	OUT14,m	OUT13,m+1	16	16	OUT13,m	OUT12,m+1	15	15	OUT12,m	OUT11,m+1	14	14	OUT11,m	OUT10,m+1	13	13	OUT10,m	OUT09,m+1	12	12	OUT09,m	OUT08,m+1	11	11	OUT08,m	+V,B	10	10	+V,A	COM1,A	9	9	COM0,A	OUT07,m+1	8	8	OUT07,m	OUT06,m+1	7	7	OUT06,m	OUT05,m+1	6	6	OUT05,m	OUT04,m+1	5	5	OUT04,m	OUT03,m+1	4	4	OUT03,m	OUT02,m+1	3	3	OUT02,m	OUT01,m+1	2	2	OUT01,m	OUT00,m+1	1	1	OUT00,m	CJ1W-MD261用 GPN-CJ28□ GPP-CJ28R□ 输入连接器 m+2CH m+3CH mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>IN00,m+2</td><td>21</td><td>21</td><td>IN00,m+3</td></tr><tr><td>IN01,m+2</td><td>22</td><td>22</td><td>IN01,m+3</td></tr><tr><td>IN02,m+2</td><td>23</td><td>23</td><td>IN02,m+3</td></tr><tr><td>IN03,m+2</td><td>24</td><td>24</td><td>IN03,m+3</td></tr><tr><td>IN04,m+2</td><td>25</td><td>25</td><td>IN04,m+3</td></tr><tr><td>IN05,m+2</td><td>26</td><td>26</td><td>IN05,m+3</td></tr><tr><td>IN06,m+2</td><td>27</td><td>27</td><td>IN06,m+3</td></tr><tr><td>IN07,m+2</td><td>28</td><td>28</td><td>IN07,m+3</td></tr><tr><td>COM2,A</td><td>29</td><td>29</td><td>COM3,A</td></tr><tr><td>IN08,m+2</td><td>30</td><td>30</td><td>IN08,m+3</td></tr><tr><td>IN09,m+2</td><td>31</td><td>31</td><td>IN09,m+3</td></tr><tr><td>IN10,m+2</td><td>32</td><td>32</td><td>IN10,m+3</td></tr><tr><td>IN11,m+2</td><td>33</td><td>33</td><td>IN11,m+3</td></tr><tr><td>IN12,m+2</td><td>34</td><td>34</td><td>IN12,m+3</td></tr><tr><td>IN13,m+2</td><td>35</td><td>35</td><td>IN13,m+3</td></tr><tr><td>IN14,m+2</td><td>36</td><td>36</td><td>IN14,m+3</td></tr><tr><td>IN15,m+2</td><td>37</td><td>37</td><td>IN15,m+3</td></tr><tr><td>COM2,B</td><td>38</td><td>38</td><td>COM3,B</td></tr><tr><td>IN16,m+2</td><td>39</td><td>39</td><td>IN16,m+3</td></tr><tr><td>IN17,m+2</td><td>40</td><td>40</td><td>IN17,m+3</td></tr><tr><td>IN18,m+2</td><td>41</td><td>41</td><td>IN18,m+3</td></tr><tr><td>IN19,m+2</td><td>42</td><td>42</td><td>IN19,m+3</td></tr><tr><td>COM2,C</td><td>43</td><td>43</td><td>COM3,C</td></tr></table> FCN插针40芯	信号名	A	B	信号名	IN00,m+2	21	21	IN00,m+3	IN01,m+2	22	22	IN01,m+3	IN02,m+2	23	23	IN02,m+3	IN03,m+2	24	24	IN03,m+3	IN04,m+2	25	25	IN04,m+3	IN05,m+2	26	26	IN05,m+3	IN06,m+2	27	27	IN06,m+3	IN07,m+2	28	28	IN07,m+3	COM2,A	29	29	COM3,A	IN08,m+2	30	30	IN08,m+3	IN09,m+2	31	31	IN09,m+3	IN10,m+2	32	32	IN10,m+3	IN11,m+2	33	33	IN11,m+3	IN12,m+2	34	34	IN12,m+3	IN13,m+2	35	35	IN13,m+3	IN14,m+2	36	36	IN14,m+3	IN15,m+2	37	37	IN15,m+3	COM2,B	38	38	COM3,B	IN16,m+2	39	39	IN16,m+3	IN17,m+2	40	40	IN17,m+3	IN18,m+2	41	41	IN18,m+3	IN19,m+2	42	42	IN19,m+3	COM2,C	43	43	COM3,C	CJ1W-ID262用 GPN-CJ49□ GPP-CJ49□ 输入连接器1 mCH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>IN00,m</td><td>36</td><td>36</td><td>IN08,m</td></tr><tr><td>IN01,m</td><td>37</td><td>37</td><td>IN07,m</td></tr><tr><td>IN02,m</td><td>38</td><td>38</td><td>IN06,m</td></tr><tr><td>IN03,m</td><td>39</td><td>39</td><td>IN05,m</td></tr><tr><td>IN04,m</td><td>40</td><td>40</td><td>IN04,m</td></tr><tr><td>IN05,m</td><td>41</td><td>41</td><td>IN03,m</td></tr><tr><td>IN06,m</td><td>42</td><td>42</td><td>IN02,m</td></tr><tr><td>IN07,m</td><td>43</td><td>43</td><td>IN01,m</td></tr><tr><td>COM0,B</td><td>44</td><td>44</td><td>COM0,A</td></tr><tr><td>IN08,m</td><td>45</td><td>45</td><td>IN07,m</td></tr><tr><td>IN09,m</td><td>46</td><td>46</td><td>IN06,m</td></tr><tr><td>IN10,m</td><td>47</td><td>47</td><td>IN05,m</td></tr><tr><td>IN11,m</td><td>48</td><td>48</td><td>IN04,m</td></tr><tr><td>IN12,m</td><td>49</td><td>49</td><td>IN03,m</td></tr><tr><td>IN13,m</td><td>50</td><td>50</td><td>IN02,m</td></tr><tr><td>IN14,m</td><td>51</td><td>51</td><td>IN01,m</td></tr><tr><td>IN15,m</td><td>52</td><td>52</td><td>IN00</td></tr></table> MIL插针40芯	信号名	A	B	信号名	IN00,m	36	36	IN08,m	IN01,m	37	37	IN07,m	IN02,m	38	38	IN06,m	IN03,m	39	39	IN05,m	IN04,m	40	40	IN04,m	IN05,m	41	41	IN03,m	IN06,m	42	42	IN02,m	IN07,m	43	43	IN01,m	COM0,B	44	44	COM0,A	IN08,m	45	45	IN07,m	IN09,m	46	46	IN06,m	IN10,m	47	47	IN05,m	IN11,m	48	48	IN04,m	IN12,m	49	49	IN03,m	IN13,m	50	50	IN02,m	IN14,m	51	51	IN01,m	IN15,m	52	52	IN00	CJ1W-ID262用 GPN-CJ49□ GPP-CJ49□ 输入连接器2 m+3CH <table><tr><td>信号名</td><td>A</td><td>B</td><td>信号名</td></tr><tr><td>COM3,A</td><td>3</td><td>4</td><td>COM3,B</td></tr><tr><td>IN15,m+3</td><td>5</td><td>6</td><td>IN07,m+3</td></tr><tr><td>IN14,m+3</td><td>7</td><td>8</td><td>IN06,m+3</td></tr><tr><td>IN13,m+3</td><td>9</td><td>10</td><td>IN05,m+3</td></tr><tr><td>IN12,m+3</td><td>11</td><td>12</td><td>IN04,m+3</td></tr><tr><td>IN11,m+3</td><td>13</td><td>14</td><td>IN03,m+3</td></tr><tr><td>IN10,m+3</td><td>15</td><td>16</td><td>IN02,m+3</td></tr><tr><td>IN09,m+3</td><td>17</td><td>18</td><td>IN01,m+3</td></tr><tr><td>IN08,m+3</td><td>19</td><td>20</td><td>IN00,m+3</td></tr><tr><td></td><td>21</td><td>21</td><td></td></tr><tr><td>COM2,A</td><td>22</td><td>22</td><td>COM2,B</td></tr><tr><td>IN15,m+2</td><td>25</td><td>26</td><td>IN07,m+2</td></tr><tr><td>IN14,m+2</td><td>27</td><td>28</td><td>IN06,m+2</td></tr><tr><td>IN13,m+2</td><td>29</td><td>30</td><td>IN05,m+2</td></tr><tr><td>IN12,m+2</td><td>31</td><td>32</td><td>IN04,m+2</td></tr><tr><td>IN11,m+2</td><td>33</td><td>34</td><td>IN</td></tr></table>	信号名	A	B	信号名	COM3,A	3	4	COM3,B	IN15,m+3	5	6	IN07,m+3	IN14,m+3	7	8	IN06,m+3	IN13,m+3	9	10	IN05,m+3	IN12,m+3	11	12	IN04,m+3	IN11,m+3	13	14	IN03,m+3	IN10,m+3	15	16	IN02,m+3	IN09,m+3	17	18	IN01,m+3	IN08,m+3	19	20	IN00,m+3		21	21		COM2,A	22	22	COM2,B	IN15,m+2	25	26	IN07,m+2	IN14,m+2	27	28	IN06,m+2	IN13,m+2	29	30	IN05,m+2	IN12,m+2	31	32	IN04,m+2	IN11,m+2	33	34	IN																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,D	20	20	+V,C																																																																																																																																																																																																																																																																																																																																																																																																																													
COM1,B	19	19	COM0,B																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT15,m+1	18	18	OUT15,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT14,m+1	17	17	OUT14,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT13,m+1	16	16	OUT13,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT12,m+1	15	15	OUT12,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT11,m+1	14	14	OUT11,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT10,m+1	13	13	OUT10,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT09,m+1	12	12	OUT09,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT08,m+1	11	11	OUT08,m																																																																																																																																																																																																																																																																																																																																																																																																																													
+V,B	10	10	+V,A																																																																																																																																																																																																																																																																																																																																																																																																																													
COM1,A	9	9	COM0,A																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT07,m+1	8	8	OUT07,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT06,m+1	7	7	OUT06,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT05,m+1	6	6	OUT05,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT04,m+1	5	5	OUT04,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT03,m+1	4	4	OUT03,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT02,m+1	3	3	OUT02,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT01,m+1	2	2	OUT01,m																																																																																																																																																																																																																																																																																																																																																																																																																													
OUT00,m+1	1	1	OUT00,m																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
IN00,m+2	21	21	IN00,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN01,m+2	22	22	IN01,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN02,m+2	23	23	IN02,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN03,m+2	24	24	IN03,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN04,m+2	25	25	IN04,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN05,m+2	26	26	IN05,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN06,m+2	27	27	IN06,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN07,m+2	28	28	IN07,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
COM2,A	29	29	COM3,A																																																																																																																																																																																																																																																																																																																																																																																																																													
IN08,m+2	30	30	IN08,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN09,m+2	31	31	IN09,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN10,m+2	32	32	IN10,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m+2	33	33	IN11,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m+2	34	34	IN12,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m+2	35	35	IN13,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m+2	36	36	IN14,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m+2	37	37	IN15,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
COM2,B	38	38	COM3,B																																																																																																																																																																																																																																																																																																																																																																																																																													
IN16,m+2	39	39	IN16,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN17,m+2	40	40	IN17,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN18,m+2	41	41	IN18,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN19,m+2	42	42	IN19,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
COM2,C	43	43	COM3,C																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
IN00,m	36	36	IN08,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN01,m	37	37	IN07,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN02,m	38	38	IN06,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN03,m	39	39	IN05,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN04,m	40	40	IN04,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN05,m	41	41	IN03,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN06,m	42	42	IN02,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN07,m	43	43	IN01,m																																																																																																																																																																																																																																																																																																																																																																																																																													
COM0,B	44	44	COM0,A																																																																																																																																																																																																																																																																																																																																																																																																																													
IN08,m	45	45	IN07,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN09,m	46	46	IN06,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN10,m	47	47	IN05,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m	48	48	IN04,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m	49	49	IN03,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m	50	50	IN02,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m	51	51	IN01,m																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m	52	52	IN00																																																																																																																																																																																																																																																																																																																																																																																																																													
信号名	A	B	信号名																																																																																																																																																																																																																																																																																																																																																																																																																													
COM3,A	3	4	COM3,B																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m+3	5	6	IN07,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m+3	7	8	IN06,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m+3	9	10	IN05,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m+3	11	12	IN04,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m+3	13	14	IN03,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN10,m+3	15	16	IN02,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN09,m+3	17	18	IN01,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
IN08,m+3	19	20	IN00,m+3																																																																																																																																																																																																																																																																																																																																																																																																																													
	21	21																																																																																																																																																																																																																																																																																																																																																																																																																														
COM2,A	22	22	COM2,B																																																																																																																																																																																																																																																																																																																																																																																																																													
IN15,m+2	25	26	IN07,m+2																																																																																																																																																																																																																																																																																																																																																																																																																													
IN14,m+2	27	28	IN06,m+2																																																																																																																																																																																																																																																																																																																																																																																																																													
IN13,m+2	29	30	IN05,m+2																																																																																																																																																																																																																																																																																																																																																																																																																													
IN12,m+2	31	32	IN04,m+2																																																																																																																																																																																																																																																																																																																																																																																																																													
IN11,m+2	33	34	IN																																																																																																																																																																																																																																																																																																																																																																																																																													

CJ1W-OD263用	
GNP-CJ57□ GPP-CJ57□ 输出连接器1 mCH 信号名 OUT00_m OUT01_m OUT02_m OUT03_m OUT04_m OUT05_m OUT06_m OUT07_m COM0_B +V_D OUT00_m+1 OUT01_m+1 OUT02_m+1 OUT03_m+1 OUT04_m+1 OUT05_m+1 OUT06_m+1 OUT07_m+1 COM1_B +V_B ▲标记 m+1CH MIL插针40芯	信号名 OUT08_m OUT09_m OUT10_m OUT11_m OUT12_m OUT13_m OUT14_m OUT15_m COM2_A +V_C OUT08_m+1 OUT09_m+1 OUT10_m+1 OUT11_m+1 OUT12_m+1 OUT13_m+1 OUT14_m+1 OUT15_m+1 COM1_A +V_A ▲标记 m+2CH MIL插针40芯

CJ1W-MD233用	
GNP-CJ45□ GPP-CJ45□ 输出连接器 mCH 信号名 OUT00 OUT01 OUT02 OUT05 OUT04 OUT06 OUT07 COM0V_B +V_B ▲标记 mCH MIL插针20芯	信号名 OUT08 OUT09 OUT10 OUT11 OUT12 OUT13 OUT14 OUT15 COM0V_A +V_A ▲标记 m+1CH MIL插针20芯

CJ1W-MD263/CJ1W-MD563用	
GNP-CJ53□ GPP-CJ53□ 输出连接器 mCH 信号名 OUT00_m OUT01_m OUT02_m OUT03_m OUT04_m OUT05_m OUT06_m OUT07_m COM0_B +V_D OUT00_m+1 OUT01_m+1 OUT02_m+1 OUT03_m+1 OUT04_m+1 OUT05_m+1 OUT06_m+1 OUT07_m+1 COM1_B +V_B ▲标记 m+1CH MIL插针40芯	信号名 OUT08_m OUT09_m OUT10_m OUT11_m OUT12_m OUT13_m OUT14_m COM0_A +V_C OUT08_m+1 OUT09_m+1 OUT10_m+1 OUT11_m+1 OUT12_m+1 OUT13_m+1 OUT14_m+1 COM1_A +V_A ▲标记 m+2CH MIL插针40芯

CJ1M-CPU22/23用	
GNP-CJ47□ GPP-CJ47□ 输入输出连接器 信号名 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 ▲标记 MIL插针40芯	信号名 A20 A19 A18 A17 A16 A15 A14 A13 A12 A11 A10 A9 A8 A7 A6 A5 A4 A3 A2 A1 ▲标记 MIL插针40芯

CJ1W-NC113用	
GNP-CJ35□ GPP-CJ35L□ 输入输出连接器 X轴 信号名 B 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 ▲标记 FCN插针40芯	信号名 A20 A19 A18 A17 A16 A15 A14 A13 A12 A11 A10 A9 A8 A7 A6 A5 A4 A3 A2 A1 ▲标记 FCN插针40芯

CJ1W-NC133用	
GNP-CJ36□ GPP-CJ36L□ 输入输出连接器 X轴 信号名 B 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 ▲标记 FCN插针40芯	信号名 A20 A19 A18 A17 A16 A15 A14 A13 A12 A11 A10 A9 A8 A7 A6 A5 A4 A3 A2 A1 ▲标记 FCN插针40芯

CJ1W-NC213用	
GNP-CJ37□ GPP-CJ37L□ 输入输出连接器 Y轴 信号名 B 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 ▲标记 FCN插针40芯	信号名 A20 A19 A18 A17 A16 A15 A14 A13 A12 A11 A10 A9 A8 A7 A6 A5 A4 A3 A2 A1 ▲标记 FCN插针40芯

CJ1W-NC233用	
GNP-CJ38□ GPP-CJ38L□ 输入输出连接器 Y轴 信号名 B 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 ▲标记 FCN插针40芯	信号名 A20 A19 A18 A17 A16 A15 A14 A13 A12 A11 A10 A9 A8 A7 A6 A5 A4 A3 A2 A1 ▲标记 FCN插针40芯

CJ1W-CT021用	
GNP-CJ34□ GPP-CJ34R□ 输入输出连接器 信号名 B20 B19 B18 B17 B16 B15 B14 B13 B12 B11 B10 B9 B8 B7 B6 B5 B4 B3 B2 B1 ▲标记 FCN插针40芯	信号名 A20 A19 A18 A17 A16 A15 A14 A13 A12 A11 A10 A9 A8 A7 A6 A5 A4 A3 A2 A1 ▲标记 FCN插针40芯

CJ1W-NC413用	
GNP-CJ39□ GPP-CJ39L□ X/Y轴连接器 Y轴 信号名 B 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 ▲标记 FCN插针40芯	信号名 A20,X/Y A19,X/Y A18,X/Y A17,X/Y A16,X/Y A15,X/Y A14,X/Y A13,X/Y A12,X/Y A11,X/Y A10,X/Y A9,X/Y A8,X/Y A7,X/Y A6,X/Y A5,X/Y A4,X/Y A3,X/Y A2,X/Y A1,X/Y ▲标记 FCN插针40芯

CJ1W-NC433用	
GNP-CJ43□ GPP-CJ43L□ X/Y轴连接器 Y轴 信号名 B 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 ▲标记 FCN插针40芯	信号名 A20,X/Y A19,X/Y A18,X/Y A17,X/Y A16,X/Y A15,X/Y A14,X/Y A13,X/Y A12,X/Y A11,X/Y A10,X/Y A9,X/Y A8,X/Y A7,X/Y A6,X/Y A5,X/Y A4,X/Y A3,X/Y A2,X/Y A1,X/Y ▲标记 FCN插针40芯

CJ1W-NC433用	
GNP-CJ44□ GPP-CJ44L□ Z/U轴连接器 U轴 信号名 B 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 ▲标记 FCN插针40芯	信号名 A20,Z/U A19,Z/U A18,Z/U A17,Z/U A16,Z/U A15,Z/U A14,Z/U A13,Z/U A12,Z/U A11,Z/U A10,Z/U A9,Z/U A8,Z/U A7,Z/U A6,Z/U A5,Z/U A4,Z/U A3,Z/U A2,Z/U A1,Z/U ▲标记 FCN插针40芯

CJ2M-MD211用	
GNP-CJ62□ 输入输出连接器 信号名 IN00N10 DC24V IN00N10 LD+ IN00N10 V0LD- IN00N12 DC24V IN00N12 V0LD- IN00N14 DC24V IN00N14 LD+ IN00N16 DC24V IN00N16 V0LD- IN00N18 DC24V IN00N18 LD+ IN00N19 LD- OUT00OUT10 OUT02OUT12 OUT04OUT14 +V_A COM_A ▲标记 MIL插针40芯	信号名 IN00N11 LD- IN00N11 V0LD- IN00N13 DC24V IN00N13 V0LD- IN00N15 DC24V IN00N15 LD+ IN00N17 DC24V IN00N17 V0LD- IN00N19 DC24V IN00N19 LD- IN00N19 LD- OUT01OUT11 OUT03OUT13 OUT05OUT15 +V_B COM_B ▲标记 MIL插针40芯

CJ2M-MD212用	
GNP-CJ63□ 输入输出连接器 信号名 IN00N10 DC24V IN00N10 LD+ IN00N10 V0LD- IN00N12 DC24V IN00N12 V0LD- IN00N14 DC24V IN00N14 LD+ IN00N16 DC24V IN00N16 V0LD- IN00N18 DC24V IN00N18 LD+ IN00N19 LD- OUT00OUT10 OUT02OUT12 OUT04OUT14 COM_A -V_A ▲标记 MIL插针40芯	信号名 IN00N11 LD- IN00N11 V0LD- IN00N13 DC24V IN00N13 V0LD- IN00N15 DC24V IN00N15 LD+ IN00N17 DC24V IN00N17 V0LD- IN00N19 DC24V IN00N19 LD- IN00N19 LD- OUT01OUT11 OUT03OUT13 OUT05OUT15 COM_B -V_B ▲标记 MIL插针40芯

*为区别相同的信号名，此处的信号名可能与PLC制造商的使用手册中的记载有少许差异，请确认后再订购。
 *无信号名标记的引脚为未接线。
 *□内填入Y或T。